

Function and channel descriptions

一、Descriptions for key function:



Menu



down



up



Enter



二、Description for menu function:

- 1、 ADDR—A001-A512
- 2、 SLND—MAST/SLAV
- 3、 AUTO—AUTO:
 - AU 1— (R)
 - AU 2— (G)
 - AU 3— (B)
 - AU 4— (W)
 - AU 5— (R+G)
 - AU 6— (R+B)
 - AU 7— (R+W)
 - AU 8— (G+R)
 - AU 8— (C+B)
 - AU 9— (R+W)
 - AU 10— (R+G+B)
 - AU 10— (R+G+W)
 - AU 11— (R+G+W)
 - AU 12— (R+G+B)
 - AU 13— (R+G+B)
 - AU 14— (R+G+B)
 - AU 15— (R+G+B)
 - AU 16— RGBW Monocolor Auto
 - AU 17— RGBW Mixed color AUTO
 - AU 18— RGBW Strobe
 - AU 19— RGBW Gradual change color
- 4、 AUSP— motor speed (SP 1 slow.....SP 8 fast)
- 5、 SOUN— SOU1/SOU2

二、Descriptions for channel function:

- CH1: 0 light beams are off, 1-255 total dimming.
- CH2: 0 light beams are off, 1-255 Red total dimming.
- CH3: 0 light beams are off, 1-255 Green total dimming.
- CH4: 0 light beams are off, 1-255 Blue total dimming.
- CH5: 0 light beams are off, 1-255 White total dimming.
- CH6: 0-15 no strobe, 16-255 strobe, speed .
- CH7: 0 light beams are off, 1-255 RGB 7color Mixed color
- CH8: 0-127 sound control of the controller is off , 128-255 sound control of the controller is on

Voltage:90-240V

Light source: RGBW

POWER:3w*4

Power consumption:30W