

# User Manual

BMBE-36

## DJ SCAN MIRROR 308



Please read this user manual before using this product.

## Features

Voltage: AC 220V 50Hz

Power: 40W

Equipped with 128pcs (64R, 40G, 24B)intensive brightness LEDs

More than 50000 hours LED life

4operation modes: Automatic running, DMX, Sound Active, Master/Slave

Sound controlled via built-in microphone

6 DMX channels

Advantages of LED-technology: extremely long life, low power consumption minimal heat emission, defacto maintenance free with brilliant light radiation

Package size: 430mm×245mm×210mm

Weight: 4kg

## INTRUCTION

Thank you for choosing DJ SCAN MIRROR 308, you will see you have acquired a powerful and versatile device.

## DIP function

ON	OFF	功能
	1 2 3 4 5 6 7 8 9 1	50 gobos auto running
9	1 2 3 4 5 6 7 8 10	Sound active,adjustable sensitive (light off when no sound).
10	1 2 3 4 5 6 7 8 9	DMX-512---6 CH ID=1
5 10	1 2 3 4 6 7 8 9	DMX-512---6 CH ID=2
6 10	1 2 3 4 5 7 8 9	DMX-512---6 CH ID=3
5 6 10	1 2 3 4 7 8 9	DMX-512---6 CH ID=4
7 10	1 2 3 4 5 6 8 9	DMX-512---6 CH ID=5
5 7 10	1 2 3 4 6 8 9	DMX-512---6 CH ID=6
.....	.....	.....

10	1 2 3 4 5 6 7 8 9	ID=1 CH1 Control GOBO A CH6 Control LED speed
1 10	2 3 4 5 6 7 8 9	ID=1 CH2 Control GOBO A CH7 Control LED speed
2 10	1 3 4 5 6 7 8 9	ID=1 CH3 Control GOBO A CH8 Control LED speed
1 2 10	3 4 5 6 7 8 9	ID=1 CH4 Control GOBO A CH9 Control LED speed
3 10	1 2 4 5 6 7 8 9	ID=1 CH5 Control GOBO A CH10 Control LED speed
1 3 10	2 4 5 6 7 8 9	ID=1 CH6 Control GOBO A CH11 Control LED speed
2 3 10	1 4 5 6 7 8 9	ID=1 CH7 Control GOBO A CH12 Control LED speed
.....	.....	.....
1 2 3 4 5 6 7 8 10	9	Master/slave

Note: when master/slave mode, the master can be Auto or Sound active, slave light will run as master one.

## Safety instruction

### CAUTION!

Be careful with your operations. With a dangerous voltage you can suffer a dangerous electric shock when touching the wires!

This device has left our premises in absolutely perfect condition. In order to maintain this condition and to ensure a safe operation, it is absolutely necessary for the user to follow the safety instructions and warning notes written in this manual.

**Please note:** Every information is subject to change without prior notice.