


CHANNELS:

channel	Channel value	function
CH1	0-127	Motor position
	128-191	Motor position infinite rotation speed from fast to slow
	192-255	Motor position infinite rotation speed from fast to slow
CH2	0	No strobe effect
	1-255	Led strobe, speed from slow to fast
CH3	0	Red led off
	1-255	Brightness red led dimming light from the dark gradually
CH4	0	Green led off
	1-255	Brightness green led dimming light from the dark gradually
CH5	0	Blue led off
	1-255	Brightness blue led dimming light from the dark gradually
CH6	0-10	CH1 to CH5 the role of
	11-33	Au01
	34-57	Au02
	58-81	Au03
	82-249	Au04
	250-255	Au010 sound effect
CH7	0-255	Led running speed setting, from fast to slow

Note

This product in the factory works good, packing integrity. All users should strictly abide by the above statement warnings and operating instructions, any damage caused by misuse, the company does not guarantee. Ignore manuals caused fault and problem also is not responsible for the dealer.

LED crystal magice ball



User Guide

UNPACKING INSTRUCTION

Unpacking:

Thanks you for purchasing this product.Please read user guide for safety and operations information before using the product.Keep this manual for future reference. Please check the attachments listed on the page after opening carton box. In the event of carton damage of attachments missing in transit,please contact your dealer or our after sales service department.

Attachment: 1. Light:1pcs 2. User Guide:1pcs 3. Power cable:1pcs

NOTICE

- 2, Do not turn on and off the unit frequently.
- 3, Makes sure the power supply connects ground before using.
- 4, This unit is applicable for only indoor use and must be avoided water,moisture and shade damage.Working temperature should be 18~30°C.
- 5, Do not use it successively over 4 hours,otherwise it will shorten its lifetime.
- 6, Use cleaning tissue to remove dust on the external lenses periodically to optimize light output.
- 7, Do not remove or break the warranty label,otherwise it void warranty.
- 8, Always replace with the exact same type fuse,replacement with anything other than the specified fuse can cause fire or electric shock and damage your unit,and will overstep our manufacture's warranty.

TECHNICAL SPECIFICATION

- 1, Voltage: AC110V,50HZ/60HZ,
- 2, Power:30W
- 3.Working Modes:Sound Active,Auto,Master-Slave
- 4.Light Source: (R:16 G:16 B:16 W:16)

FUNCTION:

feature	10	9	8	7	6	5	4	3	2	1
auto	ON	OF	OF	XX	No for slave Of not strobe	Of for 7clour jump On for shade	LED light speed setting: OF:fast ON:slowly		Dynamo speed setting: OF: slowly ON: fast	
	ON	OF	ON	On for single green	On for single blue	On for single red				
sound	ON	ON	XX	XX	XX	XX	XX	XX	XX	XX
slave	OF	OF	OF	OF	OF	OF	OF	OF	OF	NO
DMX	OF	1 to 9 for DMX address setting								