## VOLUME





The APart E-VOL20 is a 100Volt volume control. It is available in white and black color, and can handle up to 20 Watt of power.

It is very durable thanks to the step-by-step attenuation in 11 steps + zero position.

The E-VOL 20 is designed to handle 24V priority signals. This means that you can always get an announcement out, even to zones where the local volume control is in the 'OFF' position!

If your amplifier has a 24 V priority output, it will send a 24 V signal when you push the talk button on the microphone. The 24 V signal will close a relay on the E-VOL20 volume control, and the signal will pass, even when the volume control is in the 'OFF' position. This can be very useful for emergency or evacuation messages.

The E-VOL20 is built on a universal chassis that easily can be integrated with Gira, Jung and Euro. Different cover plates are available for the UK market.

## TECHNICAL SPECIFICATIONS

Type Handling Power Voltage 24 V priority Attenuation steps Build-in box Build-on box Dimensions (HxWxD) Weight color also available as

20 Watt 100 Volt Yes 11 + "0" E-MODIN E-MODON 80 x 80 x 45 mm 104 grams E-VOL20: white E-VOL20BL: black

Euro