

BIG

BM - BE - 15

Controlling via DIP-switches

Function	DIP 1	DIP 2	DIP 3	DIP 4	DIP 5	DIP 6	DIP 7	DIP 8	DIP 9	DIP 10
DMX-Mode	×	×	×	×	×	×	×	×	×	1
Slave-Mode	0	0	0	0	0	0	0	0	0	1
Master-Mode	Auto Mode	×	×	×	×	×	×	1	×	0
	Sound Mode	×	×	×	×	×	1	0	×	0
	LED Speed 1	×	×	1	1	×	×	×	×	0
	LED Speed 2	×	×	0	1	×	×	×	×	0
	LED Speed 3	×	×	1	0	×	×	×	×	0
	LED Speed 4	×	×	0	0	×	×	×	×	0
	Motor Speed 1	1	1	×	×	×	×	×	×	0
	Motor Speed 2	0	1	×	×	×	×	×	×	0
Motor Speed 3	1	0	×	×	×	×	×	×	0	
Motor Speed 4	0	0	×	×	×	×	×	×	0	

1=on 0=off ×=changeable

DMX - Protocol

Control – PAN – rotation

Channel:	Value:	Feature:
1	000 – 000	No rotation
	008 – 123	Forwards PAN-rotation with increasing speed
	124 – 131	No rotation
	132 – 247	Backwards PAN-rotation with decreasing speed
	248 - 255	No rotation

Control - LED effects

Channel:	Value:	Feature:
2	000 – 035	Dimmer
	036 – 070	Strobe
	071 – 105	Fade
	106 – 140	Color-change
	141 – 175	Color-change + Strobe
	176 – 210	Cross-fade
	211 – 255	Cross-fade + Strobe

Channel:	Value:	Feature:
3	000 – 255	Increasing speed

Channel:	Value:	Feature:
4	000 – 255	Red (0 – 100%)

Channel:	Value:	Feature:
5	000 – 255	Green (0 – 100%)

Channel:	Value:	Feature:
6	000 – 255	Blue (0 – 100%)