


LED PAR64(177pcs)



User Guide

UNPACKING INSTRUCTION

Unpacking:

Thanks you for purchasing this product.Please read user guide for safety and operations information before using the product.Keep this manual for future reference. Please check the attachments listed on the page after opening carton box. In the event of carton damage of attachments missing in transit,please contect your dealer or our after sales service department.

Attachment: 1. Light:1pcs 2. User Guide:1pcs 3. Power cable:1pcs

NOTICE

- 2, Do not turn on and off the unit frequently.
- 3, Makes sure the power supply connects ground before using.
- 4, This unit is applicable for only indoor use and must be avoided water,moisture and shade damage.Working temperature should be 18~30℃.
- 5, Do not use it successively over 4 hours,otherwise it will shorten its lifetime.
- 6, Use cleaning tissue to remove dust on the external lenses periodically to optimize light output.
- 7, Do not remove or break the warranty label,otherwise it void warranty.
- 8, Always replace with the exact same type fuse,replacement with anything other than the specified fuse can cause fire or electric shock and damage your unit,and will overstep our manufacture's warranty.

TECHNICAL SPECIFICATION

- 1, Voltage: AC110V,50HZ/60HZ,
- 2, Power:35W
- 3.Working Modes:DMX,Sound Active,Auto,Master-Slave
- 4.Light Source: ∅ 10LED 177pcs

FUNCTION:

	show	Function
1	D0001	8 channel address
2	CC00	Colores change
3	CP00	Colores change
4	DE00	Colores change
5	BEBE	Sound
6	R255	Red
7	G255	Green
8	B255	Blue

CHANNELS:

channels	value	Function
CH1	0-255	Light off
CH2	0-255	strobe
CH3	0-50	DMX channel control
	51-100	Change colors
	101-150	Change colors
	151-255	Change colors
CH4	0-255	Function speed
CH5	0-255	Red
CH6	0-255	Green
CH7	0-255	Blue

Note

This product in the factory works good, packing integrity. All users should strictly abide by the above statement warnings and operating instructions, any damage caused by misuse, the company does not guarantee. Ignore manuals caused fault and problem also is not responsible for the dealer.